



EA Electric Automation

Automation specialists

Reference: 3RT2015-1AP01

CONTACTOR, AC-3, 3KW/400V, 1NO, AC 230V, 50/60 HZ, 3-POLE, SZ S00 SCREW TERMINAL

Buy it at Electric Automation Network



product brand name	SIRIUS
Product designation	3RT2 contactor
General technical data:	
Size of contactor	500
Product extension	
function module for communication	No
Auxiliary switch	Yes
Insulation voltage	
rated value	690 V
Degree of pollution	3
Surge voltage resistance rated value	6 kV
maximum permissible voltage for safe isolation	
between coil and main contacts acc. to EN 60947-1	400 V
Protection class IP	
on the front	IP20
of the terminal	IP20
Shock resistance	
at rectangular impulse	
— at AC	6,7g / 5 ms, 4,2g / 10 ms
with sine pulse	
— at AC	10,5g / 5 ms, 6,6g / 10 ms

Mechanical service life (switching cycles)	
of contactor typical	30 000 000
of the contactor with atd>	5 000 000
of the contactor with atd>	10 000 000
Ambient conditions:	
Installation altitude at height above sea level maximum	2 000 m
Ambient temperature	
during operation	-25 +60 °C
during storage	-55 +80 °C
Main circuit:	
Number of NO contacts for main contacts	3
Number of NC contacts for main contacts	0
Operating voltage	
at AC-3 rated value maximum	690 V
Operating current	
at AC-1 at 400 V	
— at ambient temperature 40 °C rated value	18 A
at AC-1	
— up to 690 V at ambient temperature 40 °C rated value	18 A
— up to 690 V at ambient temperature 60 °C rated value	16 A
at AC-2 at 400 V rated value	7 A
at AC-3	
— at 400 V rated value	7 A
— at 500 V rated value	6 A
— at 690 V rated value	4.9 A
Connectable conductor cross-section in main circuit at AC-1	
at 60 °C minimum permissible	2.5 mm ²
at 40 °C minimum permissible	2.5 mm ²
Operating current for approx. 200000 operating cycles at AC-4	
at 400 V rated value	2.6 A
at 690 V rated value	1.8 A
Operating current	
at 1 current path at DC-1	
— at 24 V rated value	15 A
— at 110 V rated value	1.5 A
	0.6 A

— at 440 V rated value	0.42 A
— at 600 V rated value	0.42 A
with 2 current paths in series at DC-1	
— at 24 V rated value	15 A
- at 110 V rated value	8.4 A
— at 220 V rated value	1.2 A
— at 440 V rated value	0.6 A
— at 600 V rated value	0.5 A
with 3 current paths in series at DC-1	
— at 24 V rated value	15 A
— at 110 V rated value	15 A
— at 220 V rated value	15 A
— at 440 V rated value	0.9 A
— at 600 V rated value	0.7 A
Operating current	
at 1 current path at DC-3 at DC-5	
— at 24 V rated value	15 A
— at 110 V rated value	0.1 A
with 2 current paths in series at DC-3 at DC-5	
— at 110 V rated value	0.25 A
— at 24 V rated value	15 A
with 3 current paths in series at DC-3 at DC-5	
— at 110 V rated value	15 A
— at 220 V rated value	1.2 A
— at 24 V rated value	15 A
— at 440 V rated value	0.14 A
— at 600 V rated value	0.14 A
Operating power	
at AC-1	
— at 230 V rated value	6.3 kW
— at 230 V at 60 °C rated value	6 kW
— at 400 V rated value	11 kW
— at 400 V at 60 °C rated value	10.5 kW
— at 690 V rated value	19 kW
— at 690 V at 60 °C rated value	18 kW
at AC-2 at 400 V rated value	3 kW
at AC-3	

AC-4 Second	— at 400 V rated value	3 kW
AC4at 400 V rated value1.15 kWat 600 V rated value to 10 s56 APower loss (V ka AC 3 at 400 V for rated value of the perating current per conductor64 APower loss (V ka AC 3 at 400 V for rated value of the perating current per conductor1000 J/hAt AC1000 J/h1000 J/hAt AC1000 J/h1000 J/hAt AC 3 maximum1000 J/h1000 J/hAt AC 4 maximum50 J/h1000 J/hAt AC 4 maximum60 J/h1000 J/hAt AC 4 maximum60 J/h1000 J/hAt 60 Hz60 J/h <td>— at 690 V rated value</td> <td>4 kW</td>	— at 690 V rated value	4 kW
at 690 V rated value1.15 kWThermal short-time current limited to 10 s56 APower loss [W] at AC-3 at 400 V for rated value of the operating current per conductor0.4 WNo-load switching frequency0.4 Wat AC1000 1/hOperating frequency1000 1/hat AC-1 maximum1000 1/hat AC-2 maximum750 1/hat AC-3 maximum750 1/hat AC-4 maximum250 1/hControl circuit/ Control:250 1/hType of voltage of the control supply voltageACControl supply voltage at AC230 Vat 60 Hz rated value230 Vat 60 Hz rated value0.8 1.1at 50 Hz0.8 1.1Apparent pick-up power of magnet coil at AC0.8 1.1Apparent pick-up power of magnet coil at AC1.17 V/AInductive power factor with closing power of the coil3.17 V/AInductive power factor with closing power of the coil4.2 V/Aat 60 Hz0.8 1Apparent holding power of magnet coil at AC1.10Apparent holding power of magnet coil at AC1.1 V/AInductive power factor with closing power of the coil1.1 V/AInductive power of magnet coil at AC0.8 1At 50 Hz0.8 1At 50 Hz0.2 5At		
Thermal short-time current limited to 10 s56 APower loss [W] at AC-3 at 400 V for rated value of the operating current per conductor0.4 WNo-load switching frequency10 000 1/hat AC10 000 1/hOperating frequency.at AC-1 maximum1000 1/hat AC-2 maximum750 1/hat AC-3 maximum750 1/hat AC-3 maximum750 1/hat AC-4 maximum250 1/hat AC-4 maximum250 1/hat AC-4 maximum250 1/hat AC-4 maximum200 VControl forcult/ Control:.Type of voltage of the control supply voltageACControl supply voltage at AC.at 60 Hz rated value230 Vat 60 Hz rated value0.81.1at 60 Hz0.81.1Apparent pick-up power of magnet coil at AC.at 50 Hz0.81.1Apparent pick-up power of magnet coil at AC.at 60 Hz0.8.1at 60 Hz0.25at 60 Hz0.25at 60 Hz0.25at 60 Hz0.25at 60 Hz<	at 400 V rated value	1.15 kW
Power loss [W] at AC:3 at 400 V for rated value of the operating current per conductor0.4 WNo-load switching frequency10 000 1/hat AC10 000 1/hOperating frequency10 000 1/hat AC:1 maximum1000 1/hat AC:2 maximum750 1/hat AC:3 maximum250 1/hat AC:4 maximum250 1/hat AC:4 maximum250 1/hcontrol circuit/ Control:750 1/hControl circuit/ Control:750 1/hControl circuit/ Control:230 VControl supply voltage at AC230 Vat 50 Hz rated value230 VOperating range factor control supply voltage rated value of magnet coil at AC0.8 1.1at 60 Hz0.8 1.1at 60 Hz0.8 1.1Apparent pick-up power of magnet coil at AC27 V-Aat 60 Hz0.8 0.81at 60 Hz0.81at 60 Hz0.25at 60 Hz0.2	at 690 V rated value	1.15 kW
operating current per conductor0.4 WNo-load switching frequency10 000 J/hat AC10 000 J/hOperating frequency1 000 J/hat AC-1 maximum1 000 J/hat AC-2 maximum750 J/hat AC-3 maximum250 J/hat AC-4 maximum250 J/hat AC-4 maximum250 J/hcontrol circuit/ Control:Type of voltage of the control supply voltageACControl supply voltage at ACat 50 Hz rated value230 Vat 60 Hz rated value0.8 1.1at 60 Hz0.8 1.1 <trr>at 60 Hz0.8</trr>	Thermal short-time current limited to 10 s	56 A
at AC10 000 1/hOperating frequency1000 1/hat AC-1 maximum1000 1/hat AC-2 maximum750 1/hat AC-3 maximum750 1/hat AC-3 maximum750 1/hat AC-4 maximum250 1/hat AC-4 maximum250 1/hControl circuit/ Control:Type of voltage of the control supply voltageACControl supply voltage at AC230 Vat 50 Hz rated value230 VOperating range factor control supply voltage rated0.8 1.1at 60 Hz rated value0.85 1.1Apparent pick-up power of magnet coil at AC1at 50 Hz0.81at 50 Hz0.81at 50 Hz0.8at 50 Hz0.8at 60 Hz0.81at 60 Hz4.2 V Aat 60 Hz0.25at 60 Hz <td></td> <td>0.4 W</td>		0.4 W
Operating frequencyI 000 1/hat AC-1 maximum1 000 1/hat AC-2 maximum750 1/hat AC-3 maximum750 1/hat AC-4 maximum250 1/hat AC-4 maximum250 1/hControl circuit/ Control:.Type of voltage of the control supply voltageACControl supply voltage at AC230 Vat 50 Hz rated value230 VOperating range factor control supply voltage rated.value of magnet coil at AC0.81.1at 60 Hz0.851.1Apparent pick-up power of magnet coil at AC31.7 V-AInductive power factor with closing power of the coil0.8At 50 Hz0.8at 60 Hz0.8at 60 Hz0.8at 60 Hz0.8at 60 Hz0.8at 60 Hz0.8at 60 Hz0.8Apparent holding power of the coil.at 60 Hz0.8at 60 Hz0.8at 60 Hz0.8at 50 Hz0.8at 50 Hz0.8at 60 Hz0.8Apparent holding power of magnet coil at AC.at 50 Hz0.8Apparent holding power of magnet coil at AC.at 50 Hz0.8Apparent holding power of magnet coil at AC.at 50 Hz0.8Apparent holding power of magnet coil at AC.at 50 Hz0.25at 60 Hz0.25at 60 Hz0.25at 60 Hz0.25Closing delay. <td>No-load switching frequency</td> <td></td>	No-load switching frequency	
at AC-1 maximum1 000 1/hat AC-2 maximum750 1/hat AC-3 maximum750 1/hat AC-4 maximum250 1/hControl circuit/ Control:Type of voltage of the control supply voltageACControl supply voltage at ACat 50 Hz rated value230 Vat 60 Hz rated value230 VOperating range factor control supply voltage rated value of magnet coil at AC0.8 1.1at 60 Hz0.8 1.1at 60 Hz27 V-Aat 60 Hz31.7 V-Aat 60 Hz0.8 1.1At 50 Hz0.8 1.1At 50 Hz31.7 V-Aat 60 Hz0.8 1.1at 60 Hz0.8 1.1at 60 Hz31.7 V-Aat 60 Hz0.8 1.1at 60 Hz0.2 1.1at 60 Hz <t< td=""><td>at AC</td><td>10 000 1/h</td></t<>	at AC	10 000 1/h
at AC-2 maximum750 1/hat AC-3 maximum750 1/hat AC-4 maximum250 1/hControl circuit/ Control:Type of voltage of the control supply voltageACControl supply voltage at ACat 50 Hz rated value230 Vat 60 Hz rated value230 Voperating range factor control supply voltage rated value of magnet coil at ACat 50 Hz0.8 1.1at 60 Hz0.85 1.1At 60 Hz31.7 V-AInductive power factor with closing power of the coil0.8at 50 Hz0.8at 50 Hz0.8at 60 Hz0.8at 60 Hz0.8at 50 Hz0.8at 60 Hz0.25at 60	Operating frequency	
at AC-3 maximum750 1/hat AC-4 maximum250 1/hControl circuit/ Control:Type of voltage of the control supply voltageACControl supply voltage at ACat 50 Hz rated value230 Vat 60 Hz rated value230 VOperating range factor control supply voltage rated value of magnet coil at AC0.8 1.1at 50 Hz0.8 1.1at 60 Hz0.85 1.1Apparent pick-up power of magnet coil at AC31.7 V-Aat 60 Hz0.8at 50 Hz0.8at 60 Hz0.8at 50 Hz4.8 V-AInductive power factor with the holding power of the coil4.8 V-AInductive power factor with the holding power of the coil0.25at 50 Hz0.25	at AC-1 maximum	1 000 1/h
at AC-4 maximum250 1/hControl circuit/ Control:250 1/hType of voltage of the control supply voltageACControl supply voltage at AC230 Vat 50 Hz rated value230 Vat 60 Hz rated value0.8 1.1operating range factor control supply voltage rated value of magnet coil at AC0.8 1.1at 60 Hz0.8 1.1at 60 Hz0.2 1.1at 60 Hz0.25at 6	at AC-2 maximum	750 1/h
Control circuit/ Control:Type of voltage of the control supply voltageACControl supply voltage at AC230 Vat 50 Hz rated value230 Vat 60 Hz rated value230 VOperating range factor control supply voltage rated value of magnet coil at AC0.8 1.1at 60 Hz0.8 1.1at 60 Hz0.2 1.1at 60 Hz0.25at 60 Hz	at AC-3 maximum	750 1/h
Type of voltage of the control supply voltageACControl supply voltage at AC230 Vat 50 Hz rated value230 VOperating range factor control supply voltage rated value of magnet coil at AC0.8 1.1at 50 Hz0.8 1.1at 60 Hz0.85 1.1Apparent pick-up power of magnet coil at AC27 V·Aat 60 Hz31.7 V·AInductive power factor with closing power of the coil0.81at 50 Hz0.81at 50 Hz0.81at 60 Hz0.81at 60 Hz0.81at 60 Hz0.81at 60 Hz0.81Apparent holding power of magnet coil at AC0.81at 60 Hz0.81at 60 Hz0.81Apparent holding power of magnet coil at AC0.81at 60 Hz0.25at 60 Hz0.25 <tr <td="">at 60 Hz0.</tr>	at AC-4 maximum	250 1/h
Control supply voltage at AC230 Vat 50 Hz rated value230 Vat 60 Hz rated value230 VOperating range factor control supply voltage rated value of magnet coil at ACat 50 Hz0.8 1.1at 60 Hz0.8 1.1at 60 Hz0.8 1.1At 60 Hz1.1at 60 Hz1.1At 50 Hz31.7 V-Aat 60 Hz0.8at 50 Hz0.8at 60 Hz0.8at 50 Hz0.8at 50 Hz0.8at 60 Hz0.2at 60 Hz0.25at 60 Hz0.25	Control circuit/ Control:	
at 50 Hz rated value230 Vat 60 Hz rated value230 VOperating range factor control supply voltage rated value of magnet coil at AC	Type of voltage of the control supply voltage	AC
at 60 Hz rated value230 VOperating range factor control supply voltage rated value of magnet coil at ACat 50 Hz0.8 1.1at 60 Hz0.85 1.1Apparent pick-up power of magnet coil at ACat 50 Hz27 V·Aat 60 Hz31.7 V·AInductive power factor with closing power of the coil0.8at 60 Hz0.8at 60 Hz0.8at 60 Hz0.8at 60 Hz0.8at 60 Hz0.81Apparent holding power of magnet coil at AC4.2 V·Aat 60 Hz4.2 V·Aat 60 Hz0.25at 50 Hz0.25at 60 Hz0.25	Control supply voltage at AC	
Operating range factor control supply voltage rated value of magnet coil at AC 0.8 1.1 at 50 Hz 0.8 1.1 at 60 Hz 0.8 1.1 Apparent pick-up power of magnet coil at AC - at 50 Hz 27 V-A at 60 Hz 31.7 V-A Inductive power factor with closing power of the coil - at 50 Hz 0.8 at 60 Hz 0.25 at 60 Hz 0.25 at 60 Hz 0.25	at 50 Hz rated value	230 V
value of magnet coil at ACat 50 Hz0.8 1.1at 60 Hz0.85 1.1Apparent pick-up power of magnet coil at AC27 V·Aat 50 Hz31.7 V·Aat 60 Hz0.8inductive power factor with closing power of the coil0.8at 50 Hz0.8at 60 Hz0.8at 60 Hz0.8at 60 Hz0.81at 60 Hz4.2 V·Aat 60 Hz4.2 V·Aat 60 Hz0.25at 60 Hz0.25	at 60 Hz rated value	230 V
at 60 Hz0.85 1.1Apparent pick-up power of magnet coil at AC27 V·Aat 50 Hz27 V·Aat 60 Hz31.7 V·AInductive power factor with closing power of the coilat 50 Hz0.8at 60 Hz0.81Apparent holding power of magnet coil at AC4.2 V·Aat 60 Hz4.3 V·Aat 60 Hz0.25at 60 Hz0.25		
Apparent pick-up power of magnet coil at ACImage: Apparent pick-up power of magnet coil at ACat 50 Hz27 V·Aat 60 Hz31.7 V·AInductive power factor with closing power of the coilImage: Apparent holding power of the coilat 50 Hz0.8at 60 Hz0.81Apparent holding power of magnet coil at AC4.2 V·Aat 60 Hz4.8 V·AInductive power factor with the holding power of the coilImage: Apparent ACat 60 Hz0.25at 50 Hz0.25at 60 Hz0.25	at 50 Hz	0.8 1.1
At 50 Hz27 V·Aat 60 Hz31.7 V·AInductive power factor with closing power of the coil.at 50 Hz0.8at 60 Hz0.81Apparent holding power of magnet coil at AC.at 50 Hz4.2 V·Aat 60 Hz4.8 V·AInductive power factor with the holding power of the coil.at 60 Hz0.25at 50 Hz0.25col blz0.25	at 60 Hz	0.85 1.1
A t 60 Hz31.7 V-AInductive power factor with closing power of the coil.at 50 Hz0.8at 60 Hz0.81Apparent holding power of magnet coil at AC.at 50 Hz4.2 V-Aat 60 Hz4.8 V-AInductive power factor with the holding power of the coil.at 60 Hz0.25at 60 Hz0.25	Apparent pick-up power of magnet coil at AC	
Inductive power factor with closing power of the coilImage: Color of the coilat 50 Hz0.8at 60 Hz0.81Apparent holding power of magnet coil at AC4.2 V·Aat 50 Hz4.8 V·AInductive power factor with the holding power of the coil0.25at 60 Hz0.25at 60 Hz0.25	at 50 Hz	27 V·A
At 50 Hz0.8At 60 Hz0.81Apparent holding power of magnet coil at AC4.2 V·AAt 50 Hz4.2 V·AAt 60 Hz0.81Inductive power factor with the holding power of the coil0.25At 60 Hz0.25At 60 Hz0.25	at 60 Hz	31.7 V·A
At 60 Hz0.81Apparent holding power of magnet coil at AC4.2 V·Aat 50 Hz4.2 V·Aat 60 Hz4.8 V·AInductive power factor with the holding power of the coil0.25at 60 Hz0.25At 60 Hz0.25	Inductive power factor with closing power of the coil	
Apparent holding power of magnet coil at AC 4.2 V·A at 50 Hz 4.2 V·A Inductive power factor with the holding power of the coil 4.8 V·A at 50 Hz 0.25 at 60 Hz 0.25	at 50 Hz	0.8
at 50 Hz4.2 V·Aat 60 Hz4.8 V·AInductive power factor with the holding power of the coll0.25at 50 Hz0.25at 60 Hz0.25	at 60 Hz	0.81
at 60 Hz 4.8 V·A Inductive power factor with the holding power of the coil 0.25 at 50 Hz 0.25 at 60 Hz 0.25	Apparent holding power of magnet coil at AC	
Inductive power factor with the holding power of the coil at 50 Hz 0.25 at 60 Hz 0.25 Closing delay	at 50 Hz	4.2 V·A
at 50 Hz 0.25 at 60 Hz 0.25 Closing delay	at 60 Hz	4.8 V·A
at 60 Hz 0.25 Closing delay	Inductive power factor with the holding power of the coil	
Closing delay	at 50 Hz	0.25
	at 60 Hz	0.25
at AC 9 35 ms	Closing delay	
	at AC	9 35 ms

Opening delay	
at AC	3.5 14 ms
Arcing time	10 15 ms
Residual current of the electronics for control with signal <0>	
at AC at 230 V maximum permissible	3 mA
at DC at 24 V maximum permissible	10 mA
Auxiliary circuit:	
Number of NC contacts	
for auxiliary contacts	
— instantaneous contact	0
Number of NO contacts	
for auxiliary contacts	
— instantaneous contact	1
Operating current at AC-12 maximum	10 A
Operating current at AC-15	
at 230 V rated value	10 A
at 400 V rated value	3 A
at 500 V rated value	2 A
at 690 V rated value	1 A
Operating current at DC-12	
at 24 V rated value	10 A
at 48 V rated value	6 A
at 60 V rated value	6 A
at 110 V rated value	3 A
at 125 V rated value	2 A
at 220 V rated value	1 A
at 600 V rated value	0.15 A
Operating current at DC-13	
at 24 V rated value	10 A
at 48 V rated value	2 A
at 60 V rated value	2 A
at 110 V rated value	1 A
at 125 V rated value	0.9 A
at 220 V rated value	0.3 A
at 600 V rated value	0.1 A
Contact reliability of auxiliary contacts	1 faulty switching per 100 million (17 V, 1 mA)

Full-load current (FLA) for three-phase AC motor	
at 480 V rated value	4.8 A
at 600 V rated value	6.1 A
Yielded mechanical performance [hp]	
for single-phase AC motor	
— at 110/120 V rated value	0.25 hp
— at 230 V rated value	0.75 hp
for three-phase AC motor	
— at 200/208 V rated value	1.5 hp
— at 220/230 V rated value	2 hp
— at 460/480 V rated value	3 hp
— at 575/600 V rated value	5 hp
Contact rating of auxiliary contacts according to UL	A600 / Q600
Short-circuit protection	
Design of the fuse link	
for short-circuit protection of the main circuit	
- with type of coordination 1 required	gL/gG LV HRC 3NA, DIAZED 5SB, NEOZED 5SE: 35 A
— with type of assignment 2 required	gL/gG LV HRC 3NA, DIAZED 5SB, NEOZED 5SE: 20 A
for short-circuit protection of the auxiliary switch required	fuse gL/gG: 10 A
Installation/ mounting/ dimensions:	
Mounting position	+/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface
Mounting type	screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022
Side-by-side mounting	Yes
Height	58 mm
Witd>	45 mm
Depth	73 mm
Required spacing	
with side-by-side mounting	
— forwards	0 mm
— Backwards	0 mm
— upwards	0 mm
— downwards	0 mm
— at the side	0 mm
for grounded parts	
— forwards	0 mm
— Backwards	0 mm

— upwards	0 mm
— at the side	6 mm
— downwards	0 mm
for live parts	
— forwards	0 mm
— Backwards	0 mm
— upwards	0 mm
— downwards	0 mm
— at the side	6 mm
Connections/Terminals:	
Type of electrical connection	
for main current circuit	screw-type terminals
for auxiliary and control current circuit	screw-type terminals
Type of connectable conductor cross-sections	
for main contacts	
— solid	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²), 2x 4 mm²
— single or multi-stranded	2x (0,5 1,5 mm²), 2x (0,75 2,5 mm²), 2x 4 mm²
- finely stranded with core end processing	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²)
at AWG conductors for main contacts	2x (20 16), 2x (18 14), 2x 12
Type of connectable conductor cross-sections	
for auxiliary contacts	
— single or multi-stranded	2x (0,5 1,5 mm²), 2x (0,75 2,5 mm²), 2x 4 mm²
- finely stranded with core end processing	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²)
at AWG conductors for auxiliary contacts	2x (20 16), 2x (18 14), 2x 12
Safety related data:	
B10 value	
with high demand rate acc. to SN 31920	1 000 000
Proportion of dangerous failures	
with low demand rate acc. to SN 31920	40 %
with high demand rate acc. to SN 31920	73 %
Failure rate [FIT]	
with low demand rate acc. to SN 31920	100 FIT
Product function	
Mirror contact acc. to IEC 60947-4-1	Yes; with 3RH29
T1 value for proof test interval or service life acc. to IEC 61508	20 у